LOW VOLTAGE GEARMOTOR

740 - 24 Vdc

for sliding gates with max weight of 400 kg



Easy programming: self-learning

To "initialise" the automated system, just carry out the SETUP operation, selecting a suitable dipswitch. The following parameters are automatically self-learned during this operation:

- Opening/closing times
- Pause time
- Traction/thrust force
- Deceleration at end of opening and closing
- Soft Start (starting at gradual speed)

Safety: anti-crushing electronic device

Continuously controlled electronic clutch, active at both opening and closing

- Two sensitivity levels
- Movement reversed in case of an obstacle
- Emergency stop function (if clutch operates for two consecutive cycles)

Black out: emergency operation

Emergency battery (optional) ensuring operation during a power cut

Irreversible

As the gearmotor is non reversing, no electric locks need be installed and, in the event of power failure, the release device (protected by a custo-mised key) makes it possible to open and close the gate manually.



Rotating release device easy to operate and key "protected" (standard)

Cover






1 Protecting housing 2 Rotating release device easy to operate and key "protected" (standard)

У Х

2

DIMENSIONS



Technical specifications of 740 - 24 Vdc gearmotor			
Power supply	24 Vdc		
Power	70 W		
Absorbed current	3 A		
Electric motor	1.400 rpm		
Max torque	13,5 Nm		
Traction and thrust force	0 - 40 daN		
(pinion Z16)			
Pinion	Z16 module 4		
Gate speed	12 m/min.		
Operating ambient	-20°C ÷ +55°C		
temperature			
Weight	10 kg		
Limit switch	Encoder		
Protection class	IP 44		

I and the first second second

Specifications of 724 D control board (built into gearmotor or in separate container)*

	•		
Supply voltage	230 Vac (+6% -10%) 50 Hz		
of transformer			
Supply voltage of control unit	24 Vac (+6% -10%) 50 (60) Hz		
Absorbed power	3 W		
Motor maximum load	70 W		
Accessories max load	24 Vdc 500 mA		
Flashing lamp max load	24 Vdc 15 W max		
Operating ambient temperature	-20°C ÷ +55°C		
Protection fuses	3		
Function logics	Automatic/Stepped automatic/ semi-		
	automatic/Stepping semi-		
	automatic/Condo type		
Thrust force	Four levels		
	adjustable on display		
Opening/closing times	Through self-learning during		
	programming		
Pause times	Through self-learning during		
	programming		
Deceleration	Through self-learning during opening		
	and closing		
Enclosure dimensions	305x225x125 mm		
Protection class	IP 55		
Terminal board inputs - 22 Vac po	wer supply/Battery power		

Terminal board inputs - 22 Vac power supply/Battery power supply/Encoder/Total opening/Pedestrian opening/Opening-closing safety devices/Stop/Opening-closing limit-switch Terminal board outputs - 24 Vdc power supply for accessories /24 Vdc motor / 24 Vdc courtesy light-flashing lamp

Rapid connector - Card receivers/Decoding cards

inside the gearmotor (optional)*		"Remote" emergency battery kit includes (optional)*	
Voltage/current	12 V/1,2 Ah	Voltage/current	12 V/4 Ah
Dimensions	96 x 51 x 47 mm	Dimensions	90 x 70 x 108 mm
Nr. of opening/closing operations	15 max	Nr. of opening/closing operations	15 max

.

Model	Use		Control board
	Max weight (kg)	Use frequency (cycles/hour)	
740 E Z16 - 24 Vdc	400	100	724 D built-in
740 Z16 - 24 Vdc	400	100	Not included

*WARNING: The emergency battery kit cannot be installed in the gear motor. In this case, put the battery kit in the container for the 724 D electronic unit to be installed at a maximum distance of 3 m from the 740 - 24 Vdc.